TERMINAL MIX 4

How to execute a Factory Reset / Jog Wheel Reset

Step 1:
Execute a Factory Reset / Jog Wheel Reset

a) Make sure that Terminal Mix 4 is turned off

b) Hold TRAX + VIEW + PREP simultaneously and turn on the device.

Note: The device will now do a factory reset - it's important that the Terminal Mix 4 will not be touched as long as the procedure is done!

Step 2:
Set the Jog Wheel sensitivity

a) Make sure that Terminal Mix 4 is turned off

b) Hold TRAX + CRATES + BACK simultaneously and turn on the device

c) Turn the Loop MOVE encoder of the dedicated deck and adjust the sensitivity of EACH side to your preference

Notes:
› The sensitivity can be adjusted to your liking in 10 steps
› The Loop button "1/2x" is the most sensitive level
› The Sample button "4›" is the most insensitive level
› We suggest a value of "Hot Cue 3" or "Hot Cue 4"
› The current setting is displayed by an active lit LED in the Loop / Hot Cue and Sampler section

d) By pressing the Trax Encoder again, the value will be stored and your device will reboot

Note: The default value is HotCue Button 4

© Reloop 2012 // www.reloop.com