

Pioneer Dj

XDJ-XZ

PROFESSIONAL ALL-IN-ONE DJ
SYSTEM FOR REKORDBOX AND
SERATO DJ PRO

**Professional setup for events, clubs, bars,
and private studios**

NXS2-style experience

Full-size jogs with On Jog Display

Support for various media and styles

High-quality sound

Pro DJ Link

Professional effects from the DJM-900NXS2

Master output 3-band EQ

7-inch LCD touch screen

2 dedicated mic inputs with 3 band EQ

3 USB terminals

Robust, portable design

Includes rekordbox dj license

Support for Serato DJ Pro
(coming early 2020)

rekordbox dj serato DJ Pro

THE POWERHOUSE

XDJ-XZ PROFESSIONAL ALL-IN-ONE DJ SYSTEM FOR REKORDBOX AND SERATO DJ PRO

Features and user experience inherited from the NXS2 setup

SPECIFICATION

Software	rekordbox dj Serato DJ Pro (coming in early 2020)								
Frequency Response	20 Hz to 20 kHz (USB, LINE, AUX, MIC)								
S/N Ratio	114 dB (USB) 103 dB (LINE) 90 dB (PHONO) 96 dB (AUX-LINE), 90 dB (AUX-PORTABLE) 81 dB (MIC)								
Total Harmonic Distortion	0.003% (USB) 0.005% (LINE) 0.017% (PHONO)								
Input/Output Terminals	<table border="0"> <tr> <td>Inputs</td> <td>LINE × 2 (RCA) PHONO × 2 (RCA) AUX × 1 (RCA) MIC × 2 (XLR & 1/4-inch TRS jack)</td> </tr> <tr> <td>Outputs</td> <td>MASTER × 2 (XLR × 1, RCA × 1) BOOTH × 1 (1/4-inch TRS jack) PHONES × 2 (1/4-inch stereo phone jack × 1, 3.5-mm stereo mini jack × 1) SEND × 1 (1/4-inch TS jack)</td> </tr> <tr> <td>USB</td> <td>USB (Type A, 5 V/1 A) × 2 USB (Type B) × 1</td> </tr> <tr> <td>Others</td> <td>LINK × 3 (LAN 100Base-TX)</td> </tr> </table>	Inputs	LINE × 2 (RCA) PHONO × 2 (RCA) AUX × 1 (RCA) MIC × 2 (XLR & 1/4-inch TRS jack)	Outputs	MASTER × 2 (XLR × 1, RCA × 1) BOOTH × 1 (1/4-inch TRS jack) PHONES × 2 (1/4-inch stereo phone jack × 1, 3.5-mm stereo mini jack × 1) SEND × 1 (1/4-inch TS jack)	USB	USB (Type A, 5 V/1 A) × 2 USB (Type B) × 1	Others	LINK × 3 (LAN 100Base-TX)
Inputs	LINE × 2 (RCA) PHONO × 2 (RCA) AUX × 1 (RCA) MIC × 2 (XLR & 1/4-inch TRS jack)								
Outputs	MASTER × 2 (XLR × 1, RCA × 1) BOOTH × 1 (1/4-inch TRS jack) PHONES × 2 (1/4-inch stereo phone jack × 1, 3.5-mm stereo mini jack × 1) SEND × 1 (1/4-inch TS jack)								
USB	USB (Type A, 5 V/1 A) × 2 USB (Type B) × 1								
Others	LINK × 3 (LAN 100Base-TX)								
Maximum Dimensions (W × D × H)	878.0 × 466.1 × 118.4 mm / 34.6 × 18.4 × 4.7 in.								
Weight	13.0 kg / 28.7 lb								
Accessories	Power cord USB cable Operating instructions (Quick Start Guide) Software license notice rekordbox dj license key card								

REKORDBOX DJ SYSTEM REQUIREMENTS

Compatible OS	Mac	macOS Catalina 10.15 (updated to the latest version) macOS Mojave 10.14 (updated to the latest version) macOS High Sierra 10.13 (updated to the latest version) macOS Sierra 10.12 (updated to the latest version)
	Windows	Windows® 10, 8.1, 7 (the latest service pack)
CPU	Intel® processor Core™ i7, i5, i3	
Memory	4GB or more of RAM	

PRODUCT FEATURES

NXS2-STYLE EXPERIENCE

Playing on the XDJ-XZ professional all-in-one DJ system feels exactly like you're using the club standard gear.



FULL-SIZE JOGS WITH ON JOG DISPLAY

Mixing and scratching feel just like you're using the CDJ-2000NXS2, and you can keep an eye on important track information via the color screen in the center of each jog wheel.



SUPPORT FOR VARIOUS MEDIA AND STYLES

Play rekordbox-analyzed tracks from USB drives via channels 1 and 2 or connect your laptop and use rekordbox dj or even Link Export mode. With two extra channels, you can mix in audio from external sources. From early 2020, you'll also be able to perform with Serato DJ Pro.



MASTER OUTPUT 3-BAND EQ

Fine-tune your whole mix using the 3-band EQ on the master output and, with 3-band EQs on each of the mic inputs, it's easy to adjust the sound of either MC. Feedback Reducer automatically lessens the "howling" frequency if it occurs on the mic.

PROFESSIONAL EFFECTS FROM THE DJM-900NXS2

Add texture and animate your performances with all 14 Beat FX, plus the 6 Sound Color FX, from the DJM-900NXS2.



ROBUST, PORTABLE DESIGN

Take the robust XDJ-XZ wherever you want to perform. The single-unit design and grab handles make carrying and setup a breeze.



* Disclaimer: Specifications and price are subject to change.
* rekordbox is a registered trademark of Pioneer DJ Corporation.
* Serato DJ Pro and Serato DJ are registered trademarks of Serato Limited.
* Mac and macOS are trademarks of Apple Inc., registered in the U.S. and other countries.

* Windows is a registered trademark of Microsoft Corporation in the U.S. and other countries.
* Intel and Intel Core are registered trademarks of Intel Corporation in the U.S. and other countries.
* The names of companies, product names, and technology names mentioned herein are the trademarks of their respective owners.

We've made every effort to show the product accurately, but colours and typography might be different in reality. Features and specifications are correct at the time of printing but are subject to change. Please speak to your Pioneer DJ dealer to make sure the product meets your needs.

Pioneer DJ Europe Ltd | Artemis Building, Odyssey Business Park, West End Road, South Ruislip, HA4 6QE, UK | +44 (0) 203 761 7220
Pioneer DJ Americas, Inc | 2050 W. 190th Street, Suite 109, CA 90504, Torrance, USA | +1 (424) 488-0480
Pioneer DJ Corporation | 6-F, Yokohama i-Mark Place, 4-4-5 Minatomirai, Nishi-ku, Yokohama, Kanagawa 220-0012 Japan | +81 045-522-5400