

Pioneer Dj

OPUS-QUAD

PROFESSIONAL ALL-IN-ONE DJ SYSTEM

- Harmony of design and playability
- Standalone 4-deck playback
- Easy-to-use pro effects
- Support for multiple media sources
- Rapid and accurate track search
- Zone output
- Optimized deck configuration
- Smart Cue
- High-quality sound
- rekordbox and Serato[®]1 compatibility

rekordbox

serato DJ Pro



The Art of Sound

OPUS-QUAD

THE ART OF SOUND

OPUS-QUAD: PROFESSIONAL ALL-IN-ONE DJ SYSTEM

SPECIFICATIONS

Input/Output terminals	Inputs	LINE / PHONO x 2 (RCA) MIC x 2 (XLR & 1/4" TRS jack)
	Outputs	MASTER x 2 (XLR x 1, RCA x 1) ZONE x 1 (XLR x 1) BOOTH x 1 (1/4" TRS jack) PHONES x 2 (1/4" stereo jack x 1, 3.5 mm stereo mini jack x 1)
USB	USB	USB Type-A x 3 USB Type-C x 1
	Others	LAN terminal (1000BASE-T) x 1
Wireless LAN	Supported standards	IEEE 802.11 a / b / g / n / ac
	Frequency band used	2.4 GHz / 5 GHz
Bluetooth	Wireless system	Bluetooth ver. 4.2
	Compatible codecs	SBC, AAC
Software	rekordbox for Mac/Windows	rekordbox for iOS/Android (Coming April 2023)
	Serato DJ Pro (Coming summer 2023)	
Frequency response		20 Hz - 20 kHz
S/N ratio		114 dB (USB-MASTER1)
Total Harmonic Distortion		0.003% (USB-MASTER1)
Power supply		AC 100 V, 50 Hz / 60 Hz
Power consumption		60 W
Maximum dimensions (W x D x H)		925.7 x 499.7 x 142 mm / 36.44" x 19.67" x 5.59"
Weight		13.2 kg / 29.1 lb
Accessories		Power cord
		Quick Start Guide Precautions for use



Visit the official rekordbox website for the software's specifications: rekordbox.com




Visit the official Serato website for the specifications of Serato DJ Pro: serato.com

PRODUCT FEATURES

HARMONY OF DESIGN AND PLAYABILITY

With a radiating shape that features a sloping top plate and curved edge at the front, the OPUS-QUAD is designed to not only look sophisticated, but also to enable comfortable and intuitive operation. And, with a matte black finish and earth-colored slits on the front and sides, it can enhance the aesthetic of any environment.




STANDALONE 4-DECK PLAYBACK

Play 4 tracks on 4 different decks simultaneously, cue up tracks in advance, or leave a deck free for dropping requests into your set at a moment's notice – all with just one unit. You can even assign a different color to each deck, which is matched by the jog ring illumination.



EASY-TO-USE PRO EFFECTS

The XY-Pad makes it easy to control features such as FX Bank and channel select, as Beat FX parameters and the cut-off frequency of the filter are controlled by movement on the X and Y-axis respectively so you can blend both effects with a single finger. There are also the popular Smooth Echo and Sound Color FX features to get creative with.



SUPPORT FOR MULTIPLE MEDIA SOURCES

Connect USB thumb drives, a huge SSD drive, PC/Macs running DJ software, rekordbox for iOS/Android on a smartphone via Wi-Fi², or even a Bluetooth device. The OPUS-QUAD offers so much connectivity, you can draw from various music libraries.

RAPID AND ACCURATE TRACK SEARCH

Find your tracks faster and more accurately than ever with the freshly designed user interface featuring a 10.1-inch touch screen with access to Playlist Bank, a keyboard, and Touch Preview. There's also a new Smart Rotary Selector to get hands-on with.



ZONE OUTPUT

Thanks to the zone output – which can output sound that's separate from the master – you can play different music in different rooms from a single OPUS-QUAD.



¹ From summer 2023.
² From April 2023.

* Disclaimer: Specifications and price are subject to change. | * Pioneer DJ is a trademark of PIONEER CORPORATION and is used under license. | * rekordbox™ is a trademark or registered trademark of AlphaTheta Corporation. | * Serato DJ Pro is a registered trademark of Serato Limited.
* iPhone, iPad, iPod touch, iTunes, Mac, and macOS are registered trademarks of Apple Inc. in the U.S. and other countries. | * iOS is a trademark containing Cisco trademark signs in the U.S. and other countries. | * Android is a trademark of Google LLC.
* The Bluetooth®/MD word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by AlphaTheta Corporation is under license. Other trademarks and trade names are those of their respective owners. | * Wi-Fi is a registered trademark of Wi-Fi Alliance®.
* Mac and macOS are trademarks of Apple Inc., registered in the U.S. and other countries. | * Other product, technology, and company names, etc. mentioned herein are trademarks or registered trademarks of their respective owners.

AlphaTheta EMEA Limited | Unit 39, Tileyard Studios, Tileyard Road, London, N7 9AH, UK | +44 (0) 203 761 7220
AlphaTheta Music Americas, Inc. | 2050 W. 190th Street, Suite 109, CA 90504, Torrance, USA | +1 (424) 488-0480
AlphaTheta Corporation | 6-F, Yokohama i-Mark Place, 4-4-5 Minatomirai, Nishi-ku, Yokohama, Kanagawa 220-0012 Japan | +81 045-522-5400

PIONEERDJ.COM

